



Mic 2 Priority Mute



Media Player With Bluetooth And USB, AM/FM Tuner



Zone Volume Control

Experience Superior Sound with Our Class AB Mixing Amplifiers

Powerful Performance: Choose between 200W and 500W models for crystal-clear audio that resonates.
Connect & Play: Bluetooth, USB, SD card, and radio - your music, your way.
Zone-Specific Volume Control: Unique 5-zone control at your fingertips

Suitable Applications:

1. Entertainment Venues: Customize audio settings for distinct areas.
2. Retail Environments: Create the desired atmosphere in different store sections.
3. Cafés and Restaurants: Modulate ambiance from energetic to intimate settings.
4. Industrial Sites: Ensure clarity in announcements despite background noise.

Rear View Panel:-



Technical Specification:-

Model	MA5200	MA5500
Rated Output / Keluaran Dinilai	200 Watt	500 Watt
Power Source / Sumber Kuasa	AC220V -240V (50hz -60hz)	
AC Power Consumption (Approximate) / Penggunaan Kuasa AC (Anggaran)	351 Watt	877 Watt
Frequency Response / Tindak Balas Frekuensi	40hz - 16khz (+/- 2dB)	
Speaker Output (Zone 1 - Zone5) / Keluaran Pembesar Suara (Zon 1 - Zon 5)	100V Line Only	
Speaker Output(All Out terminal) / Keluaran Pembesar Suara (Terminal Keluar Semua)	High Impedance 100V Line	
	Low Impedance 4Ω-16Ω	
Mic Input (-52dB) / Input Mikrofon (-52dB)	Mic 1 & Mic 2	
Line Input (-10dB) / Input Talian (-10dB)	RCA Left Right - Line 1 Line 2, Line 3	
S/N Ratio / Nisbah S/N	Over 80dB	
Line Output (+4dB) / Keluaran Talian (+4dB)	RCA Left Right	
Weight / Keberatan	7.25 Kg	
Dimensions / Dimensi	481mm (W) x 100mm(H) x 338mm (D)	
Accessories / Aksesori	Come with 0.5 meter RCA to mini jack cable	